

Code: AMD-103

WIRELESS MAGNETIC DETECTOR **AMD-103** SATEL

Wireless, magnetic doors or windows opening detector. The detector is "the first line of object protection", by which the alarm system responds to the intrusion even before the intruder will be able to get inside the protected area. It is perfect to create surveillance system in small-size buildings, such as e.g.: kiosks, summer houses, boutiques, freestanding garages and workshops, and wherever conducting wire installation is difficult or impossible to perform.

The AMD-103 supports the other devices compatible with wireless ABAX system.

Lithium battery to power the device ensures many years of work without having to replace it, so the system is as easy to get along in life as traditional wired solutions.



Detection:	Opening the door or window
Frequency band:	868 MHz ... 868.6 MHz
Radio communication range (at open area):	max. 350 m
Support:	Satel ABAX
Alarm signaling:	Signal to control panel
Tamper contact:	✓
Battery:	CR2477N
Backup time:	max. 2 years
Current consumption:	14 mA
Protection class (Grade):	—
Environmental class EN 50130-5:	II
Main features:	<ul style="list-style-type: none"> • LED for zone state indication • Tamper detection - opening the enclosure, removing from mounting surface
Operation temp:	-10 °C ... 55 °C
Permissible relative humidity:	93 ± 3 %
Color:	White
Weight:	0.04 kg



DATA SHEET

Dimensions:	32 x 45 x 20 mm
Manufacturer / Brand:	SATEL
Guarantee:	2 years

