

Code: BCS-NVR16045ME-P

NVR **BCS-NVR16045ME-P** 16 CHANNELS +16-PORT SWITCH POE



Standard:	TCP/IP
Supported resolutions:	16 @ 2592 x 1944 px, 16 @ 2048 x 1536 px, 16 @ 1920 x 1080 px, 16 @ 1280 x 960 px, 16 @ 1280 x 720 px, 16 @ 704 x 576 px
Video outputs:	1 pcs HDMI 1 pcs VGA 1 pcs BNC
Audio support:	16 Channels - Audio from cameras
Audio inputs:	1 pcs Microphone - CINCH
Audio outputs:	1 pcs - CINCH
Image compression method:	H.264 / MJPEG
Maximal total frame rate:	400 fps @ 2592 x 1944 px, 400 fps @ 2048 x 1536 px, 400 fps @ 1920 x 1080 px, 400 fps @ 1280 x 960 px, 400 fps @ 1280 x 720 px, 400 fps @ 704 x 576 px
Supported hard drives:	4 x 6 TB SATA + 4 x 2 TB eSATA - HDD Array
Recording modes:	Manual, Sensor, Motion detection, Schedule
Network protocols:	HTTP, UPNP, RTSP,SMTP, NTP, DHCP, DNS, PPPOE, DDNS, FTP, ONVIF 2.0
External storage devices backup:	Backup to USB drive (pendrive, external drive) HDD Array eSATA
Searching and playback the records:	Records searching: by time and events type. Records playback: forward, backward, fast, slow "Frame by Frame" playback function All channels synchronous playback, Smart Search function
Bitrate:	200 Mbps
Network functions:	Full support via network, Remote records copying, Web-Server built-in max. 120 on-line users

Mobile phones support:	Port no.: 37777 or access by a cloud (P2P) • Android: Free application DMSS • iOS (iPhone): Free application DMSS • Windows Phone: Free application wDMSS Lite There are also paid versions of mobile applications: gDMSS Plus, iDMSS Plus, wDMSS plus
Alarm inputs / outputs:	16 pcs / 4 pcs
PTZ control:	RS-485 - Many protocols
Motion Detection:	22 x 18 motion zones 6 sensitivity levels
Mouse support:	✓
IR remote controller in the set:	✓
Switch PoE:	16-port PoE Switch built-in, 15,4 W / Channel, PoE (802.3af) Cooperation with cameras with DHCP function activated
Power supply:	230 V AC
Weight:	4.73 kg
Dimensions:	440 x 420 x 75 mm
Supported languages:	Polish, English
Country of origin:	China
Manufacturer / Brand:	BCS
Guarantee:	2 years