

Code: LE-402063

## RESIDUAL CURRENT CIRCUIT BREAKER **LE-402063** THREE-PHASE, AC TYPE 30 mA 40 A LEGRAND

Residual current circuit breaker with rated sensitivity of  $I_{\Delta n} = 30\text{mA}$ , AC type. The LE-402063 circuit breaker is compatible to DIN TS-35 rail mounting system.



|                           |                                                        |
|---------------------------|--------------------------------------------------------|
| Device type:              | Residual current circuit breaker, Three-phase, AC type |
| Rated sensitivity:        | 30 mA                                                  |
| Rated current:            | 40 A                                                   |
| Number of poles:          | 4                                                      |
| Breaking capacity:        | 10000 A                                                |
| Rated voltage:            | 400 V AC / 50 Hz                                       |
| Connectors type:          | screw terminals                                        |
| Housing:                  | Plastic, DIN, TS-35 rail mounting                      |
| Width in 17.5 mm modules: | 4                                                      |
| Weight:                   | 0.308 kg                                               |
| Dimensions:               | 71 x 83 x 75 mm                                        |
| Manufacturer / Brand:     | LEGRAND                                                |
| Guarantee:                | 2 years                                                |