

Code: HDMI-SW-2/1P-POP

## MULTI-VIEWER SWITCHER **HDMI-SW-2/1P-POP**

The image multi-viewer switcher allows to select one or several signal sources and connect them to the output. In addition, the device can work as a vertical image splitter, allowing simultaneous display the image from two HDMI sources with the option of selecting an active audio channel.

Remote controller included in the kit.



Number of HDMI inputs:	2 pcs
Number of HDMI outputs:	1 pcs
Supported HDMI standard:	1.3b
Supported audio formats:	LPCM, Dolby-AC3, DTS7.1, Dolby True HD, DTS-HD
Max. power consumption:	12 W
Maximal transmission range:	≤ 15 m
Supported resolutions:	480i, 480p, 576i, 576p, 720p, 1080i, 1080p / 50 Hz, 1080p / 60 Hz
HDCP:	✓
Power supply:	12 V / 2 A (power adapter included)
Main features:	<ul style="list-style-type: none"> <li>• Vertical image splitter from two sources</li> <li>• The ability to choose one of the two audio sources</li> <li>• Remote control - included</li> </ul>
Weight:	0.322 kg
Dimensions:	149 x 103 x 22 mm
Guarantee:	2 years