

## DATA SHEET

Code: MV-512

## MULTISWITCH MV-512 5 INPUTS / 12 OUTPUTS TERRA

Radial multiswitches from MV series are dedicated for medium and large SMATV systems with distribution of SAT IF and terrestrial TV signals, however they can also be used in smaller installations.

The MV-512 multiswitch has an active (amplified) line for terrestrial and satellite TV. The adjustment of the gain (signal level) for each SAT IF and DVB-T lines is made with dedicated switches.

Die-cast housing guarantees high screening efficiency class  $\boldsymbol{A}$ .



Inputs:	4x 950 MHz 2400 MHz , 1x 47 MHz 862 MHz - Active
Outputs:	12x 47 MHz 2400 MHz
Switching signals:	14 V / 18 V 0 Hz / 22 kHz
SAT amplification (cable pre-correction):	3 14 dB
TV amplification (cable pre-correction):	-3 5 dB
SAT Gain control:	12 dB by 4 dB step
TV Gain control:	15 dB by 1 dB step
Isolation:	<ul> <li>Between inputs SAT/SAT ≥ 30 dB</li> <li>Outputs ≥ 30 dB SAT</li> <li>Outputs ≥ 35 dB DVB-T</li> </ul>
Maximal output level SAT:	105 dBμV
Maximal output level TV:	84 88 dBµV
Pre-amplifiers powering:	-
Power supply:	Inputs HL/HH Power adapter 18 V DC / 1 A (not included)
Dimensions:	227 x 135 x 30 mm
Weight:	0.64 kg
Manufacturer / Brand:	TERRA
Guarantee:	2 years