

Code: MXD-300-BR

MULTIPURPOSE WIRELESS DETECTOR **MXD-300-BR** SATEL

The MXD-300-BR detector is a multifunctional device that can work as: magnetic, magnetic with roller shutter input, shock, shock and magnetic, water flood detector.

The detector working with MICRA alarm control panel based on software version 2.02 or later.

Attention! The detector is sold without the FPX-1 flood probe, which is available separately in our offer.



Detection:	• Opening the door or window, • Shocks, Vibrations, • Water
Frequency band:	433.05 MHz ... 434.79 MHz
Radio communication range (at open area):	≤ 600 m - PERFECTA ≤ 500 m - VERSA-MCU / MTX-300 / MICRA ≤ 300 m - MRU-300
Support:	Satel MICRA
Alarm signaling:	• Signal to control panel • LED indicator
Tamper contact:	✓
Battery:	CR123A 3 V (included)
Backup time:	max. 2 years
Current consumption:	≤ 22 mA
Protection class (Grade):	2
Environmental class EN 50130-5:	II

Main features:	• detecting the presence of water in spaces where there is a risk of leakage • detection of shocks and vibrations accompanying attempts to force a door or window open • detection of opening doors, windows, etc. (magnetic detector) • input for connecting a NC type wired detector • input for connecting a wired roller shutter detector • battery diagnostics • Encrypted radio communication in the 433 MHz frequency band • Tamper detection - opening the enclosure, removing from mounting surface
Operation temp:	-10 °C ... 55 °C
Permissible relative humidity:	93 ± 3 %
Color:	Brown
Weight:	0.04 kg
Dimensions:	24 x 110 x 27 mm
Manufacturer / Brand:	SATEL
Guarantee:	2 years