

Code: MC16-PAC-ST-4-KIT

ACCESS CONTROLLER **MC16-PAC-ST-4-KIT** ROGER

The MC16-PAC-ST-4-KIT access control kit is designed to support 4 doors in the RACS 5 v2 ver. ST system. The kit includes a metal enclosure with a power supply and a networked access controller.



Number of served transitions:	4 (two-way)
Number of supported readers:	16
Number of users:	unlimited (purchase of the appropriate license required)
Number of media per ID:	8 - Proximity card, PIN code, fingerprint, etc.
Buffer memory:	8 000 000 events buffer
Number of access zones:	8
Number of alarm zones:	8
Battery backup support:	12 V / 20 Ah
Communication:	• Ethernet - RJ-45 socket • RACS 5 v2 (Roger) • RS-485 interface

Main features:	• Metal housing • The MCX4D I/O expander included • Integrated support in VISO ST software • Functions in the VISO ST system: - MSSQL database - work in distributed systems - multi-station work - monitoring of transitions with video preview - T&A event reporting - maximum number of transitions in the system : 128
Power supply:	• 17 ... 22 V AC • 10 ... 15 V DC • 22 ... 26 V DC
Operation temp:	5 °C ... 40 °C
Permissible relative humidity:	10 % ... 95 % (non-condensing)
Weight:	4.05 kg
Dimensions:	405 x 365 x 120 mm
Manufacturer / Brand:	ROGER
Guarantee:	3 years