

Code: GATEBOX/BLEBOX

SMART GATE AND DOOR CONTROLLER **GATEBOX/BLEBOX** Wi-Fi, 12 ... 24 V DC/AC

The GATEBOX/BLEBOX controller enables remote opening and closing of swing gates, sliding gates, garage gates and doors. The device is enough to be attached to the gate operator or electric lock to be able to safely control gates and doors. Control is possible using a physical switch, a web browser, an external BleBox µWiFi controller or the wBox mobile application.

To work with full functionality, the device requires connection to a home Wi-Fi network. Controlling BleBox devices via the cloud requires additionally connecting the home network to the Internet and enabling the "Remote access" function in the device configuration.

Voice control allows you to control the device via voice commands from Amazon Alexa or the Google Assistant (Internet access required).

Attention! The control current must not exceed 20 mA per output. Overloading the output will cause irreparable damage to the controller.



Application:	swing gates, sliding gates, garage gates, doors
Rated voltage:	12 ... 24 V DC/AC
Maximal total load:	—
Total maximal current:	20 mA / Control output
Number of inputs:	2
Number of outputs:	2
Connector type:	screw terminals
Wireless:	Wi-Fi, 2.4 GHz - IEEE 802.11g
Mobile phones support:	- The wBox free application on Android - The wBox free application on iOS
Main features:	- Control of the electric strike and automatic gate, - Multiple users support from anywhere, - Control many objects from one app, - remote access, - voice control, - µWiFi technology support



DATA SHEET

Housing:	Plastic
"Index of Protection":	IP20
Color:	Black
Operation temp:	-20 °C ... 50 °C
Weight:	0.03 kg
Dimensions:	50 x 34 x 18 mm
Manufacturer / Brand:	BleBox
Guarantee:	2 years

