

## DATA SHEET

## Code: MP-2/R ADJUSTABLE AUDIO MODULE **MP-2/R**

The MP-2/R is designed to listen to sound from the surroundings and operate with DVRs. Module was made in SMD technology for further mounting, eg in camera bracket. The device has the microphone directly mounted on the PCB, and gain control PCB potentiometer. There are soldering points on the PCB to solder the module connecting wires.



Bandwidth:	20 Hz 18 kHz
S/N ratio:	$\geq 60 \text{ dB}$
Operation area:	5 150 m <sup>2</sup>
Gain adjustment:	1x 500x
Power supply:	12 V DC
Microphone:	on the preamplifier PCB
Output impedance:	600 Ω - Coaxial cable
Current consumption:	5 mA
Housing:	-
Dimensions:	19 x 24 x 9 mm
Weight:	0.003 kg
Manufacturer / Brand:	DELTA
Guarantee:	3 years

