

Code: KONW/QUAD-INVERTO+TV

TV-SAT LNB **KONW/QUAD-INVERTO+TV**

The KONW/QUAD-INVERTO+TV is a combination of the standard Quad LNB (4 independent FullBand LNBs in one housing), the RTV splitter and TV-SAT multiplexer. On the KONW/QUAD-INVERTO+TV LNB outputs there is RTV-SAT "mixed" signal, which can be distributed to 4 outlets.



Type:	Quad
Input frequency:	• 10.7 GHz ... 11.7 GHz • 11.7 GHz ... 12.75 GHz
Output frequency:	• 950 - 1950 MHz • 1100 - 2150 MHz
Oscillator frequency:	9.75 GHz / 10.6 GHz
S/N ratio:	0.2 dB
Number of outputs:	4 pcs F socket
Output impedance:	75 Ω
LNB switch:	—
Gain :	50 - 65 dB
H/V polarization switching:	13 / 18 V
Band switching:	22 kHz
Recommended dish diameter:	75 - 90 cm
Neck diameter:	40 mm
TV frequency range:	47 ... 862 MHz
RTV band loss:	8 dB
Operation temp:	-30 °C ... +60 °C
Manufacturer / Brand:	INVERTO
Weight:	0.317 kg
Dimensions:	143 x 110 x 75 mm



DATA SHEET

Guarantee:

2 years