

Code: BCS-DVR-KN-II

IP / RS-485 KEYBOARD CONTROLLER **BCS-DVR-KN-II**

Network keyboard with full possibilities of controlling and programming the PTZ camera heads of the BCS-SD series. It is also possible to control many DVRs from one keyboard.



Protocols:	Pelco-D, Pelco-P, DH-SD, PELCO-D1, PELCO-P1, BCS-DVR - DH1/DH2
Cameras numbers (ID):	1 ... 255
Maximal control distance:	1200 m @ RS-485 / RS-232
Communication standard:	<ul style="list-style-type: none"> Ethernet - RJ45 RS-485 - terminals RS-232 - terminals
Manipulator:	3-axis joystick, Speed proportional to the swing (possibility of zoom control by joystick)
Display:	LCD - with light indication
PTZ control:	<ul style="list-style-type: none"> RS-485 interface - BCS or other manufacturers Speed Dome cameras RJ-45 socket - BCS only
Power supply:	12 V DC / 0.42 A
Operation temp. / Relative humidity:	-10 °C ... 55 °C / max. 90 % non-condensing
Weight:	0.67 kg
Dimensions:	330 x 160 x 110 mm
Manufacturer / Brand:	BCS
Guarantee:	3 years