

Code: ISC-BPR2-W12

PIR DETECTOR **ISC-BPR2-W12** BOSCH

Digital passive PIR detector.



Application:	Indoor
Pyroelectric sensor:	Double
Sensor type:	Passive Infra Red (PIR)
Range:	12 x 12 m
Sensitivity adjustment:	—
Pet immunity:	—
Maximal outputs load:	100 mA / 25 V DC
Digital temperature compensation:	✓
Power supply:	12 V DC / 9 mA
Operation temp:	-10 °C ... 55 °C
Weight:	0.08 kg
Dimensions:	60 x 105 x 43 mm
Manufacturer / Brand:	BOSCH
Guarantee:	2 years