

Code: RAW-104

ANTENNA AMPLIFIER **RAW-104** 6 / 9 dB

The RAW-104 is used to TV signal distribution in home antennas installations.
Amplifier can be powered directly from included power adapter or via output with using a separator.



Frequency range:	87.8 MHz ... 862 MHz
Number of inputs/outputs:	1 / 4
Input/output impedance:	75 Ω
Connectors type:	"F"
Gain :	6 / 9 dB
Gain adjustment:	—
S/N ratio:	< 3 dB
Maximum output level:	95 dBμV
IMA3 60dB:	89 dBμV
IMA2 60dB:	76 dBμV
Return loss:	≥ 10 dB
Pre-amplifiers powering:	—
Operation temp:	-25 °C ... 55 °C
Power supply:	12 V DC / 45 mA
Weight:	0.1 kg
Dimensions:	112 x 64 x 29 mm
Guarantee:	2 years